

# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

## Features

- Output Voltage Range: 1.0V to 5.0V (selectable in 100mV steps)
- Highly Accurate:  $\pm 2\%$
- Dropout Voltage: 0.17V @ 100mA (3.3V type)
- High Ripple Rejection: 70dB (10 kHz)
- Low Power Consumption: 70 $\mu$ A (TYP.)
- Maximum Output Current : 300mA
- Standby Current : less than 2 $\mu$ A
- Internal protector: current limiter
- Internal discharge MOS
- SOT-23-5L ,DFNWB1x1-4L,SOT-353 and SOT-343 package

## Applications

- Mobile phones
- Cordless phones
- Cameras, Video cameras
- Portable games
- Portable AV equipment
- Reference voltage
- Battery powered equipment


## General Description

The TX6211C series are highly precise, low noise, positive voltage LDO regulators manufactured using CMOS processes. The series achieves high ripple rejection and low dropout and consists of a standard voltage source, an error correction, current limiter and a phase compensation circuit plus a driver transistor. Output voltage is selectable in 100mV increments within a range of 1.5V ~ 5.0V. The series is also compatible with low

ESR ceramic capacitors which give added output stability. This stability can be maintained even during load fluctuations due to the excellent transient response of the series.

The current limiter's feedback circuit also operates as a short protect for the output current limiter and the output pin. The CE function enables the output to be turned off, resulting in greatly reduced power consumption.

## Typical Application Circuit



**Caution:** 1. The above connection diagram and constant will not guarantee successful operation. Perform thorough evaluation using the actual application to set the constant.

2. Input capacitor (CIN): 1.0 $\mu$ F or more, Output capacitor (COUT): 1.0 $\mu$ F or more (tantalum capacitor)

3. A general series regulator may oscillate, depending on the external components selected. Check that no oscillation occurs with the application using the above capacitor.


# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

## Order Information

TX6211C①②③④⑤⑥


Designator	Symbol	Description	Designator	Symbol	Description
①		CE Pin Logic :	⑤		Package Type :
	A	Active 'High' (pull-down resistor built in)		M	SOT-23-5L
	B	Active 'High' (no pull-down resistor built in)		K	SOT-353
	C	Active 'Low' (pull-up resistor built in)		C	SOT-343
	D	Active 'Low' (no pull-up resistor built in)		D	DFNWB1*1-4L
②③	10-60	Output Voltage: e.g. 20 = 2.0V 30 = 3.0V etc.			
		⑥		Device Orientation :	
④	2		Output Voltage : 100mV increments e.g. ②=3, ③=8, ④=2 represents 3.8V	R	Embossed Tape : Standard Feed
	A		Output Voltage : 50mV increments e.g. ②=3, ③=8, ④=A represents 3.85V	L	Embossed Tape : Reverse Feed

## Block Diagram



# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

## Pin configuration



## Pin Assignment

Pin Number			Pin Name	Function
SOT-23-5L /SOT-353	DFNWB1*1-4L	SOT-343		
1	4	4	VIN	Supply power
2	2	2	GND	Ground
3	3	1	CE	Enable pin
4	-	-	NC	NC
5	1	3	VOUT	Voltage output

## Marking Rule

- SOT-23-5L, SOT-353, SOT-343



① Represents the product name

Symbol	Product Name
4	TX6211C◆◆◆◆◆◆

② Represents the type of regulator

Voltage(V)	1.0~3.0	3.1~6.0	1.05~3.05	3.15~6.05	Product Name
Symbol	V	A	E	L	TX6211CA◆◆◆◆◆◆
	X	B	F	M	TX6211CB◆◆◆◆◆◆
	Y	C	H	N	TX6211CC◆◆◆◆◆◆
	Z	D	K	P	TX6211CD◆◆◆◆◆◆

# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

③ Represents the Output Voltage


Symbol	Output Voltage(V)			
0		3.1		3.15
1		3.2		3.25
2		3.3		3.35
3		3.4		3.45
4		3.5		3.55
5		3.6		3.65
6		3.7		3.75
7		3.8		3.85
8		3.9		3.95
9	1.0	4.0	1.05	4.05
A	1.1	4.1	1.15	4.15
B	1.2	4.2	1.25	4.25
C	1.3	4.3	1.35	4.35
D	1.4	4.4	1.45	4.45
E	1.5	4.5	1.55	4.55

Symbol	Output Voltage(V)			
F	1.6	4.6	1.65	4.65
H	1.7	4.7	1.75	4.75
K	1.8	4.8	1.85	4.85
L	1.9	4.9	1.95	4.95
M	2.0	5.0	2.05	5.05
N	2.1		2.15	
P	2.2		2.25	
R	2.3		2.35	
S	2.4		2.45	
T	2.5		2.55	
U	2.6		2.65	
V	2.7		2.75	
X	2.8		2.85	
Y	2.9		2.95	
Z	3.0		3.05	

④ Represents the assembly lot no.

0~9, A~Z repeated (G, I, J, O, Q, W excepted)

- WBFBP1X1-4L



① Represents the Output Voltage

Symbol	Voltage(V)	Symbol	Voltage(V)	Symbol	Voltage(V)	Symbol	Voltage(V)
A	1.1	K	2.1	U	3.1	5	4.1
B	1.2	L	2.2	V	3.2	6	4.2
C	1.3	M	2.3	W	3.3	7	4.3
D	1.4	N	2.4	X	3.4	8	4.4
E	1.5	O	2.5	Y	3.5	9	4.5
F	1.6	P	2.6	Z	3.6	+	4.6
G	1.7	Q	2.7	1	3.7	-	4.7
H	1.8	R	2.8	2	3.8	*	4.8
I	1.9	S	2.9	3	3.9	?	4.9
J	2.0	T	3.0	4	4.0	=	5.0

②Represents the assembly lot No.

0~9, A~Z repeated (G, I, J, O, Q, W excepted)

# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

## Absolute Maximum Ratings

Parameter	Symbol	Maximum Rating		Unit
Input Voltage	V <sub>IN</sub>	V <sub>SS</sub> -0.3~V <sub>SS</sub> +8		V
	V <sub>ON/OFF</sub>	V <sub>SS</sub> -0.3~V <sub>IN</sub> +0.3		
Output Voltage	V <sub>OUT</sub>	V <sub>SS</sub> -0.3~V <sub>IN</sub> +0.3		mW
Power Dissipation	P <sub>D</sub>	SOT-23-5L	400	
		SOT-353,SOT-343	250	
		DFNWB1*1-4L	100	
Operating Ambient Temperature	T <sub>opr</sub>	-40~-+85		°C
Storage Temperature	T <sub>stg</sub>	-40~-+125		

**Caution:** The absolute maximum ratings are rated values exceeding which the product could suffer physical damage. These values must therefore not be exceeded under any conditions.


## Electrical Characteristics

Parameter	Symbol	Condition	Min	Typ	Max	Unit
Output Voltage	V <sub>OUT(E)</sub>	V <sub>IN</sub> =V <sub>OUT(S)</sub> +1.0 V, I <sub>OUT</sub> =30 mA	V <sub>OUT(S)</sub> x0.98	V <sub>OUT(S)</sub>	V <sub>OUT(S)</sub> x1.02	V
Output Current	I <sub>OUT</sub>	V <sub>IN</sub> ≥V <sub>OUT(S)</sub> +1.0 V	300	-	-	mA
Dropout Voltage	V <sub>drop</sub>	I <sub>OUT</sub> =50 mA	-	0.12	0.20	V
		I <sub>OUT</sub> =100 mA	-	0.30	0.45	
Line Regulations	$\frac{\Delta V_{OUT1}}{\Delta V_{IN} \bullet V_{OUT}}$	V <sub>OUT(S)</sub> +0.5 V ≤ V <sub>IN</sub> ≤7 V I <sub>OUT</sub> =30 mA	-	0.10	0.2	%/V
Load Regulation	ΔV <sub>OUT2</sub>	V <sub>IN</sub> =V <sub>OUT(S)</sub> +1.0 V 1.0 mA ≤ I <sub>OUT</sub> ≤ 100 mA	-	50	100	mV
Output Voltage Temperature Characteristics	$\frac{\Delta V_{OUT}}{\Delta T_a \bullet V_{OUT}}$	V <sub>IN</sub> =V <sub>OUT(S)</sub> +1.0 V, I <sub>OUT</sub> =10 mA -40°C ≤ T <sub>a</sub> ≤ 85°C	-	±100	-	ppm/°C
Supply Current	I <sub>SS1</sub>	V <sub>IN</sub> =V <sub>OUT(S)</sub> +1.0 V	-	70	-	μA
Input Voltage	V <sub>IN</sub>	-	2.0	-	7.0	V
Ripple-Rejection	PSRR	V <sub>IN</sub> =V <sub>OUT(S)</sub> +1.0 V, f=10 kHz V <sub>rip</sub> =0.5 Vrms, I <sub>OUT</sub> =50 mA	-	70	-	dB
Short-circuit Current	I <sub>short</sub>	V <sub>IN</sub> =V <sub>OUT(S)</sub> +1.0 V, V <sub>CE</sub> on V <sub>OUT</sub> =gnd	-	40	-	mA
CE "High" Voltage	V <sub>CEH</sub>	-	1.6	-	-	V
CE "Low" Voltage	V <sub>CEL</sub>	-	-	-	0.8	V
CE "High" Current (no resistor built in)	I <sub>CEH</sub>	V <sub>IN</sub> =V <sub>CCE</sub> =V <sub>OUT(T)</sub> +1.0V	-0.1	-	0.1	uA
CE "Low" Current (no resistor built in)	I <sub>CEL</sub>	V <sub>IN</sub> =V <sub>OUT(T)</sub> +1.0V, V <sub>CCE</sub> =V <sub>SS</sub>	-0.1	-	0.1	uA
Inrush Current	I <sub>RUSH</sub>	V <sub>IN</sub> =V <sub>OUT(T)</sub> +1V, CL=47uF, V <sub>CE</sub> =0 →V <sub>OUT(T)</sub> +1V(Only when rising and within 1ms)			800	mA


# ***TX6211C High Speed Low Dropout Middle Current Voltage Regulators***

## Typical Performance Characteristics


1. Quiescent Current VS Input Voltage




2. Output Voltage VS Input Voltage




3. Output Current Limit VS Input Voltage




4. GND Pin Current VS Input Voltage



5. GND Pin Current VS Output Current




6. Quiescent Current VS Temperature




# TX6211C High Speed Low Dropout Middle Current Voltage Regulators


## 7. Output Current Limit VS Temperature




## 8. Output Voltage VS Temperature




## 9. Dropout Voltage VS Temperature




## 10. CE "High" Voltage VS Temperature






## 11. CE "Low" Voltage VS Temperature



## 12. Load Regulation VS Temperature




# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

13. Input voltage transient response ( $IL=30mA$ )14. Load transient response ( $IL=0-350-0mA$ )15. Load transient response ( $IL=10-350-10mA$ )16. Ripple-Rejection ( $IL=50mA$ ,  $V_{pp}=1V$ ,  $F=1KHZ$ )


17. CE Opening Time



18. CE Turn-off Time




19. Inrush Current



# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

## Package Information

- SOT-23-5L




Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.050	1.250	0.041	0.049
A1	0.000	0.100	0.000	0.004
A2	1.050	1.150	0.041	0.045
b	0.300	0.500	0.012	0.020
c	0.100	0.200	0.004	0.008
D	2.820	3.020	0.111	0.119
E	1.500	1.700	0.059	0.067
E1	2.650	2.950	0.104	0.116
e	0.950(BSC)		0.037(BSC)	
e1	1.800	2.000	0.071	0.079
L	0.300	0.600	0.012	0.024
θ	0°	8°	0°	8°


# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

---


- DFNWB1.8x2-6L



Top View



Bottom View





Side View

Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	0.450/0.550	0.550/0.650	0.180/0.022	0.022/0.026
A1	0.000	0.050	0.000	0.002
A3	0.150REF		0.006REF	
D	1.724	1.876	0.068	0.074
E	1.924	2.076	0.076	0.082
D1	13000	1.500	0.051	0.059
E1	0.800	1.000	0.031	0.039
k	0.200MIN		0.008MIN	
b	0.180	0.280	0.007	0.011
e	0.500TYP		0.020TYP	
L	0.174	0.326	0.007	0.013

# TX6211C High Speed Low Dropout Middle Current Voltage Regulators


- SOT-353



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	0.900	1.100	0.035	0.043
A1	0.000	0.100	0.000	0.004
A2	0.900	1.000	0.035	0.039
b	0.150	0.350	0.006	0.014
c	0.080	0.150	0.003	0.006
D	2.000	2.200	0.079	0.087
E	1.150	1.350	0.045	0.053
E1	2.150	2.450	0.085	0.096
e	0.650TYP		0.026TYP	
e1	1.200	1.400	0.047	0.055
L	0.525REF		0.021REF	
L1	0.260	0.460	0.010	0.018
θ	0°	8°	0°	8°

# TX6211C High Speed Low Dropout Middle Current Voltage Regulators

- SOT-343



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	0.900	1.100	0.035	0.043
A1	0.000	0.100	0.000	0.004
A2	0.900	1.000	0.035	0.039
b	0.150	0.350	0.006	0.014
c	0.080	0.150	0.003	0.006
D	2.000	2.200	0.079	0.087
E	1.150	1.350	0.045	0.053
E1	2.150	2.450	0.085	0.096
e	0.650TYP		0.026TYP	
e1	1.200	1.400	0.047	0.055
L	0.525REF		0.021REF	
L1	0.260	0.460	0.010	0.018
θ	0°	8°	0°	8°

***TX6211C High Speed Low Dropout  
Middle Current Voltage Regulators***

---

© Shenzhen MEIRIT Micro-Electronics Tech Co., Ltd

TX cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a TX product. No circuit patent license, copyrights or other intellectual property rights are implied. TX reserves the right to make changes to their products or specifications without notice. Customers are advised to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete.