

# 3-TERMINAL 1.5A POSITIVE ADJUSTABLE VOLTAGE REGULATOR





## DESCRIPTION

The LM317 is an adjustable 3-terminal positive voltage regulator designed to supply more than 1.5A of Output current with voltage adjustable from 1.3V-37V.

## FEATURES

- Output current up to 1.5A
- Output voltage adjustable from 1.3V to 37V
- Internal short circuit protection
- Internal over temperature protection
- Safe-area compensation for output transistor

## PIN DESCRIPTION



## ABSOLUTE MAXIMUM RATINGS

(Ta=25°C, UNLESS OTHERWISE SPECIFIED)

PARAMETERS	SYMBOL	RATING	UNITS
Input-Output Voltage Difference	V <sub>I</sub> -V <sub>O</sub>	40	V
Lead Temperature	T <sub>LEAD</sub>	260	°C
Power Dissipation	P <sub>D</sub>	Internal Limited	-
Operating Temperature Range	T <sub>OPR</sub>	0~+125	°C
Storage Temperature Range	T <sub>STG</sub>	-60~+150	°C

## ELECTRICAL CHARACTERISTICS

(V<sub>I</sub>-V<sub>O</sub>=5V, 0< T<sub>j</sub><125°C, I<sub>O</sub>=500mA, I<sub>max</sub>=1.5A, P<sub>max</sub>=20W, UNLESS OTHERWISE SPECIFIED)

PARAMETER	SYMBOL	TEST CONDLTIONS	MIN	TYP	MAX	UNIT
Line regulation	△V <sub>O</sub>	T <sub>a</sub> =25°C, 3V≤V <sub>I</sub> -V <sub>O</sub> ≤40V		0.01	0.04	%/V
		T <sub>a</sub> =0-125°C, 3V≤V <sub>I</sub> -V <sub>O</sub> ≤40V		0.02	0.07	
Load Regulation	△V <sub>O</sub>	T <sub>a</sub> =25°C 10mA≤I <sub>O</sub> ≤I <sub>max</sub>	V <sub>O</sub> ≤6V	18	25	mV
			V <sub>O</sub> ≤5V	0.4	0.5	%/V <sub>O</sub>
	△V <sub>O</sub>	10mA≤I <sub>O</sub> ≤I <sub>max</sub>	V <sub>O</sub> ≤5V	40	70	mV
			V <sub>O</sub> ≤5V	0.8	1.5	%/V <sub>O</sub>
Adjustable Pin Current	I <sub>ADJ</sub>			46	100	uA
Adjustable Pin Current Change	△I <sub>ADJ</sub>	2.5V≤V <sub>I</sub> -V <sub>O</sub> ≤40V, 10mA≤I <sub>O</sub> ≤I <sub>max</sub> , P <sub>D</sub> ≤P <sub>max</sub>		2.0	5	uA
Reference Voltage	V <sub>REF</sub>	3V≤V <sub>I</sub> -V <sub>O</sub> ≤40V, 10mA≤I <sub>O</sub> ≤I <sub>max</sub> , P <sub>D</sub> ≤P <sub>max</sub>	1.2	1.25	1.3	V
Temperature Stability	STT			0.7		%/V <sub>O</sub>
Minimum Load Current for regulation	I <sub>L(MIN)</sub>	V <sub>I</sub> -V <sub>O</sub> =40V		3.5	10	mA
Maximum output Current	I <sub>O(MAX)</sub>	V <sub>I</sub> -V <sub>O</sub> =15V, P <sub>D</sub> ≤P <sub>max</sub>	1.5	2.2		A
		V <sub>I</sub> -V <sub>O</sub> =15V, P <sub>D</sub> ≤P <sub>max</sub> , T <sub>a</sub> =25°C	0.15	0.4		
RMS Noise v.s.%of V <sub>out</sub>	e <sub>N</sub>	T <sub>a</sub> =25°C, 10Hz≤F≤10KHz		0.003	0.01	%/V <sub>O</sub>
Ripple Rejection	RR	V <sub>O</sub> =10V, F=120Hz, C <sub>adj</sub> =0		60		dB
		V <sub>O</sub> =10V, F=120Hz, C <sub>adj</sub> =10uF	66	75		
Load-term Stability, T <sub>j</sub> =T <sub>HIGH</sub>	ST	T <sub>a</sub> =25°C, 1000 hr		0.3	1	%

Note: Testing with low duty pulse should be used to avoid heating effect.

## Important statement:

Huaguan Semiconductor Co,Ltd. reserves the right to change the products and services provided without notice. Customers should obtain the latest relevant information before ordering, and verify the timeliness and accuracy of this information.

Customers are responsible for complying with safety standards and taking safety measures when using our products for system design and machine manufacturing to avoid potential risks that may result in personal injury or property damage.

Our products are not licensed for applications in life support, military, aerospace, etc., so we do not bear the consequences of the application of these products in these fields.

Our documentation is only permitted to be copied without any tampering with the content, so we do not accept any responsibility or liability for the altered documents.