



FEATURES

- J-STD-020D reflow
- RoHS compliant
- Maxim MAX253 compatible
- 3.3V and 5V versions
- Isolation to 4kVDC
- Frequency range to 500kHz
- Toroidal construction
- Industry-standard pinout
- UL 94 V-0 package materials
- Low profile
- Industrial temperature range

DESCRIPTION

The 78253 series of converter transformers are specifically designed for use with the MAX253 chip set to provide isolated power supplies. The 5V input version can supply 1W and the 3.3V input version can supply 500mW. A centre tapped secondary winding allows for full bridge, half bridge or voltage doubling.

For through hole versions see 78253 series datasheet.

78253J Series

MAX253 Compatible Converter SM Transformers

SELECTION GUIDE						
Order Code	Input Voltage			Output rent	lsolation Voltage	Turns
	V	V	r	A	VDC	Ratio
78253/35JC	3.3	5.0	1	00	1500	1:2.27
78253/55JC	5.0	5.0	20	00	1500	1:1.31
78253/35JVC	3.3	5.0	1	00	4000	1:2.14
78253/55JVC	5.0	5.0	20	00	4000	1:1.33
ORDER CODE DETAILS						
Order Code	Package Type		Packaging Type		Quantity	
78253/XXJ(V)C	6 Pin Sl	N	Tube		50	
78253/XXJ(V)C-R	6 Pin SM		Tape & Reel		500	
78253/35JC CHARACTER	ISTICS					
Parameter	Conditions		Min.	Тур.	Max.	Units
Primary Inductance, L _P	100kHz, 250mV		0.27	0.36	0.50	mH
Secondary Inductance, L _s	100kHz, 250mV		1.60	2.00	2.40	mH
Leakage Inductance, L	100kHz, 250mV			0.32	1.00	μH
Interwinding Capacitance, C _w				24	50	pF
Primary D.C. Resistance, R _{DC}	>0.1VDC			0.5	1.00	Ω
Volt-time Product, Et	Pins 1/2	or 2/3	30	49		Vµs
78253/55JC CHARACTER	ISTICS					
Parameter	Conditio	ns	Min.	Тур.	Max.	Units
Primary Inductance, L _P	100kHz,	250mV	0.57	0.83	1.10	mH
Secondary Inductance, L _s	100kHz,		1.10	1.40	1.70	mH
Leakage Inductance, L	100kHz,			0.51	1.00	μΗ
Interwinding Capacitance, C _{ww} 100kHz, 2				30	50	pF
Primary D.C. Resistance, R _{DC} >0.1VDC				0.70	1.50	Ω
Volt-time Product, Et	Volt-time Product, Et Pins 1/2 o		40	70		Vµs
78253/35JVC CHARACTE						
Parameter	Conditio	ns	Min.	Тур.	Max.	Units
Primary Inductance, L _P	100kHz,		110	142	203	μH
Secondary Inductance, L _s 100kHz, 2			550	710	850	μH
Leakage Inductance, L				3.46	5.00	μH
Interwinding Capacitance, C _w				2	8.00	pF
Primary D.C. Resistance, R _{DC}	>0.1VDC			0.30	0.50	Ω
Volt-time Product, Et	Pins 1/2	or 2/3	18	30		Vµs
78253/55JVC CHARACTE						
Parameter	Conditio		Min.	Тур.	Max.	Units
Primary Inductance, L _P	100kHz, 20mV		170	240	335	μH
Secondary Inductance, L _s	100kHz, 20mV		350	444	540	μH
Leakage Inductance, L _L	100kHz, 250mV			6.28	8.00	μH
Interwinding Capacitance, $C_{_{WV}}$				3.4	8.00	pF
Primary D.C. Resistance, R _{DC}				0.40	0.60	Ω
Volt-time Product, Et	Pins 1/2	or 2/3	25	37		Vµs

All specifications typical at $T_A=25^{\circ}C$




www.murata.com

78253J Series

MAX253 Compatible Converter SM Transformers


ABSOLUTE MAXIMUM RATINGS				
Operating free air temperature range	-40°C to 85°C			
Storage temperature range	-50°C to 125°C			
Peak current I _{PK}	400mA			
Isolation voltage 78253/XXJC (flash tested for 1 second)	1500Vpc			
Isolation voltage 78253/XXJVC (flash tested for 1 second)	4000Vpc			

PACKAGE SPECIFICATIONS



78253J Series

MAX253 Compatible Converter SM Transformers




All curves are derived from testing with the Maxim MAX235 IC using the circuit shown in application note MPAN-03 (download at http://www.murata-ps.com/data/apnotes/mpan-03.pdf).

www.murata.com

78253J Series

MAX253 Compatible Converter SM Transformers



TECHNICAL NOTES

ISOLATION VOLTAGE

'Hi Pot Test', 'Flash Tested', 'Withstand Voltage', 'Proof Voltage', 'Dielectric Withstand Voltage' & 'Isolation Test Voltage' are all terms that relate to the same thing, a test voltage, applied for a specified time, across a component designed to provide electrical isolation, to verify the integrity of that isolation.

All products in this series are 100% production tested at their stated isolation voltage.

A question commonly asked is, "What is the continuous voltage that can be applied across the part in normal operation?"

For a part holding no specific agency approvals both input and output should normally be maintained within SELV limits i.e. less than 42.4V peak, or 60VDC. The isolation test voltage represents a measure of immunity to transient voltages and the part should never be used as an element of a safety isolation system. The part could be expected to function correctly with several hundred volts offset applied continuously across the isolation barrier; but then the circuitry on both sides of the barrier must be regarded as operating at an unsafe voltage and further isolation/insulation systems must form a barrier between these circuits and any user-accessible circuitry according to safety standard requirements.

REPEATED HIGH-VOLTAGE ISOLATION TESTING


It is well known that repeated high-voltage isolation testing of a barrier component can actually degrade isolation capability, to a lesser or greater degree depending on materials. construction and environment. This series has toroidal isolation transformers. with no additional insulation between primary and secondary windings of enamelled wire. While parts can be expected to withstand several times the stated test voltage, the isolation capability does depend on the wire insulation. Any material, including this enamel (typically polyurethane) is susceptible to eventual chemical degradation when subject to very high applied voltages thus implying that the number of tests should be strictly limited. We therefore strongly advise against repeated high voltage isolation testing, but if it is absolutely required, that the voltage be reduced by 20% from specified test voltage.

This consideration equally applies to agency recognised parts rated for better than functional isolation where the wire enamel insulation is always supplemented by a further insulation system of physical spacing or barriers.

SOLDERING INFORMATION¹

Pin finish	Matte tin
Max. peak reflow temperature	245°C
Moisture sensitivity level ²	1
Max. time above liquidous (217 °C)	100s

TUBE OUTLINE DIMENSIONS




All specifications typical at $T_{A}=25^{\circ}C$

- 1 For further information, please visit www.murata-ps.com/rohs
- 2 Representative samples of the product were subjected to the conditioning described in IPC/JEDEC J-STD-020D and passed electrical testing, package coplanarity and visual inspection which revealed no external cracks or changes in package body flatness.

www.murata.com

78253J Series

MAX253 Compatible Converter SM Transformers



www.murata.com

2021-03-11 KMP_78253JC_B01 Page 5 of 6

78253J Series

MAX253 Compatible Converter SM Transformers

DISCLAIMER

Unless otherwise stated in the datasheet, all products are designed for standard commercial and industrial applications and NOT for safety-critical and/or life-critical applications.

Particularly for safety-critical and/or life-critical applications, i.e. applications that may directly endanger or cause the loss of life, inflict bodily harm and/or loss or severe damage to equipment/property, and severely harm the environment, a prior explicit written approval from Murata is strictly required. Any use of Murata standard products for any safety-critical, life-critical or any related applications without any prior explicit written approval from Murata shall be deemed unauthorised use.

These applications include but are not limited to:

- Aircraft equipment
- Aerospace equipment
- Undersea equipment
- Power plant control equipment
- Medical equipment
- Transportation equipment (automobiles, trains, ships, etc.)
- Traffic signal equipment
- Disaster prevention / crime prevention equipment
- Data Processing equipment

Murata makes no express or implied warranty, representation, or guarantee of suitability, fitness for any particular use/purpose and/or compatibility with any application or device of the buyer, nor does Murata assume any liability whatsoever arising out of unauthorised use of any Murata product for the application of the buyer. The suitability, fitness for any particular use/purpose and/or compatibility of Murata product with any application or device of the buyer remain to be the responsibility and liability of the buyer.

Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards that anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm, and take appropriate remedial actions. Buyer will fully indemnify and hold Murata, its affiliated companies, and its representatives harmless against any damages arising out of unauthorised use of any Murata products in any safety-critical and/ or life-critical applications.

Remark: Murata in this section refers to Murata Manufacturing Company and its affiliated companies worldwide including, but not limited to, Murata Power Solutions.



This product is subject to the following <u>operating requirements</u> and the <u>Life and Safety Critical Application Sales Policy</u>: Refer to: https://www.murata.com/en-eu/products/power/requirements

Murata Power Solutions (Milton Keynes) Ltd. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in cance therevith. Specifications are subject to change without notice. © 2021 Murata Power Solutions (Milton Keynes) Ltd