



BSS84W

P-CHANNEL ENHANCEMENT MODE FIELD EFFECT TRANSISTOR

Product Summary

BV _{DSS}	R _{DS(ON)}	I _D T _A = +25°C
-50V	$10\Omega @ V_{GS} = -5V$	-130mA

Description

This MOSFET has been designed to minimize the on-state resistance ($R_{DS(ON)}$) and yet maintain superior switching performance, making it ideal for high efficiency power management applications.

Applications

- General Purpose Interfacing Switch
- Power Management Functions
- Analog Switch

Features

- Low On-Resistance
- Low Gate Threshold Voltage
- Low Input Capacitance
- · Fast Switching Speed
- Totally Lead-Free & Fully RoHS Compliant (Notes 1 & 2)
- Halogen and Antimony Free. "Green" Device (Note 3)
- Qualified to AEC-Q101 Standards for High Reliability
- PPAP Capable (Note 4)


Mechanical Data

- Case: SOT323
- Case Material: Molded Plastic, "Green" Molding Compound, UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020
- Terminal Connections: See Diagram
- Terminals: Solderable per MIL-STD-202, Method 208
 Lead Free Plating (Matte Tin Finish Annealed over Alloy 42
 Leadframe). (3)
- Weight: 0.006 grams (Approximate)






Top View



Equivalent Circuit



Top View


Ordering Information (Notes 4 & 5)

Part Number	Compliance	Case	Packaging
BSS84W-7-F	Standard	SOT323	3000 / Tape & Reel
BSS84WQ-7-F	Automotive	SOT323	3000 / Tape & Reel

Notes:

- 1. No purposely added lead. Fully EU Directive 2002/95/EC (RoHS), 2011/65/EU (RoHS 2) & 2015/863/EU (RoHS 3) compliant.
- 2. See https://www.diodes.com/quality/lead-free/ for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.
- 3. Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.
- 4. Automotive products are AEC-Q101 qualified and are PPAP capable. Automotive, AEC-Q101 and standard products are electrically and thermally the same, except where specified. For more information, please refer to https://www.diodes.com/quality/.
- 5. For packaging details, go to our website at https://www.diodes.com/design/support/packaging/diodes-packaging/.

Marking Information



K84 = Product Type Marking Code YM or \overline{Y} M = Date Code Marking Y or \overline{Y} = Year (ex: F = 2018) M = Month (ex: 9 = September)

Shanghai A/T Site

Date Code Key

Year	2012	2	~		2018	20	19	2020		2021	2	2022
Code	Z		~		F	(3	Н				J
Month	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code	1	2	3	4	5	6	7	8	9	0	N	D



Maximum Ratings (@ $T_A = +25$ °C, unless otherwise specified.)

Characteristic	Symbol	Value	Unit	
Drain-Source Voltage		V _{DSS}	-50	V
Drain-Gate Voltage (Note 6)		V_{DGR}	-50	V
Gate-Source Voltage	Continuous	V _{GSS}	±20	V
Drain Current (Note 6)	Continuous	I _D	-130	mA
Pulsed Drain Current (Note 6)		I _{DM}	-1	A

Thermal Characteristics

Characteristic	Symbol	Value	Unit
Total Power Dissipation (Note 6)	P _D	200	mW
Thermal Resistance, Junction to Ambient	R _{0JA}	625	°C/W
Operating and Storage Temperature Range	T _J , T _{STG}	-55 to +150	°C

Electrical Characteristics (@T_A = +25°C, unless otherwise specified.)

Characteristic	Symbol	Min	Тур	Max	Unit	Test Condition		
DFF CHARACTERISTICS (Note 7)								
Drain-Source Breakdown Voltage	BV _{DSS}	-50	-75		V	$V_{GS} = 0V, I_D = -250\mu A$		
Zero Gate Voltage Drain Current	I _{DSS}			-1 -2 -100	μΑ μΑ nA	V _{DS} = -50V, V _{GS} = 0V, T _J = +25°C V _{DS} = -50V, V _{GS} = 0V, T _J = +125°C V _{DS} = -25V, V _{GS} = 0V, T _J = +25°C		
Gate-Body Leakage	I _{GSS}			±10	nA	$V_{GS} = \pm 20V, V_{DS} = 0V$		
ON CHARACTERISTICS (Note 7)	ON CHARACTERISTICS (Note 7)							
Gate Threshold Voltage	V _{GS(TH)}	-0.8	-1.6	-2.0	V	$V_{DS} = V_{GS}$, $I_D = -1mA$		
Static Drain-Source On-Resistance	R _{DS(ON)}		6	10	Ω	$V_{GS} = -5V, I_D = -0.1A$		
Forward Transconductance	g FS	0.05	_	_	S	V _{DS} = -25V, I _D = -0.1A		
DYNAMIC CHARACTERISTICS								
Input Capacitance	Ciss			45	pF			
Output Capacitance	Coss	_	_	25	pF	$V_{DS} = -25V, V_{GS} = 0V, f = 1.0MHz$		
Reverse Transfer Capacitance	Crss	_	_	12	pF			
SWITCHING CHARACTERISTICS								
Turn-On Delay Time	t _{D(ON)}		10	_	ns	$V_{DD} = -30V$, $I_D = -0.27A$,		
Turn-Off Delay Time	t _{D(OFF)}	_	18	_	ns	$R_{GEN} = 50\Omega$, $V_{GS} = -10V$		

6. Device mounted on FR-4 PCB, 1 inch x 0.85 inch x 0.062 inch; pad layout as shown on Diodes Incorporated's suggested pad layout document, which can be found on our website at http://www.diodes.com/package-outlines.html.

7. Short duration pulse test used to minimize self-heating effect.







Fig. 1 Max Power Dissipation vs. Ambient Temperature






Fig. 5 On-Resistance vs. Junction Temperature





Fig. 2 Drain Source Current vs.Drain Source Voltage



V_{GS}, GATE-SOURCE VOLTAGE (V) Fig. 4 On-Resistance vs. Gate-Source Voltage





Fig. 6 On-Resistance vs. Drain-Current



Package Outline Dimensions

Please see http://www.diodes.com/package-outlines.html for the latest version.

SOT323




SOT323						
Dim	Min	Max	Тур			
A1	0.00	0.10	0.05			
A2	0.90	1.00	0.95			
b	0.25	0.40	0.30			
С	0.10	0.18	0.11			
D	1.80	2.20	2.15			
Е	2.00	2.20	2.10			
E1	1.15	1.35	1.30			
е	0.650 BSC					
e1	1.20	1.40	1.30			
F	0.375	0.475	0.425			
١	0.25	0.40	0.30			
а	0°	8°				
All Dimensions in mm						

Suggested Pad Layout

Please see http://www.diodes.com/package-outlines.html for the latest version.

SOT323



Dimensions	Value (in mm)
С	0.650
G	1.300
Х	0.470
Υ	0.600
Y1	2.500



IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
 - 1. are intended to implant into the body, or
 - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2018, Diodes Incorporated

www.diodes.com