


# PIN RECEPTACLES

FOR .032" - .046" DIAMETER PINS

## 0327/0351/0373

**03XX-0-15-XX-34-XX-10-0**  
Solder mount in .075 min. mounting hole  
Also available on 12mm or 24mm wide carrier tape: See chart for details  
See page 194.11 for Tape & Reel details




Basic Part Number	Length L	Depth N
0327-0	.206	.180
0351-0	.226	.200
0373-0	.270	.241

### T&R Packaging

Basic Part Number	Tape Width	Parts per 13" Reel
0327-0	12mm	1,400
0351-0	24mm	1,100
0373-0	24mm	1,000


## 0328

**0328-0-15-XX-34-XX-10-0**  
Hex press-fit in .079 plated through-hole




## 0334

**0334-0-15-XX-34-XX-10-0**  
Hex press-fit in .079 plated through-hole




## 0312

**0312-0-15-XX-34-XX-10-0**  
Solder mount in .075 min. mounting hole  
Also available on 12mm wide carrier tape: 1,400 parts per 13" reel  
See page 194.11 for Tape & Reel details




## 0333

**0333-0-42-XX-34-XX-10-0**  
Press-fit in .076 mounting hole




## 0357

**0357-0-15-XX-34-XX-10-0**  
Press-fit in .078 mounting hole




## 0317

**0317-0-15-XX-34-XX-04-0**  
Solder mount in .091 min. mounting hole




## 0340

**0340-0-15-XX-34-XX-10-0**  
Solder mount in .087 min. mounting hole  
Also available on 24mm wide carrier tape: 1,250 parts per 13" reel  
See page 194.11 for Tape & Reel details




## 0345

**0345-0-15-XX-34-XX-10-0**  
Press-fit in .089 mounting hole




## 0316

**0316-0-15-XX-34-XX-10-0**  
Solder mount in .087 min. mounting hole



## 0314

**0314-0-15-XX-34-XX-10-0**  
Solder mount in .087 min. mounting hole



### SPECIFICATIONS:

**Shell Material:** Brass Alloy 360, 1/2 Hard

**Contact Material:** Beryllium Copper Alloy 172, HT

**Dimensions:** Inches

**Tolerances On:** Lengths: ±.005

Diameters: ±.002

Angles: ± 2°



**ORDER CODE:** XXXX - X - XX - XX - 34 - XX - 10 - 0

**BASIC PART #**

**SPECIFY SHELL FINISH:**

01 200 μ" TIN/LEAD OVER NICKEL

◆ 80 200 μ" TIN OVER NICKEL (RoHS)

◆ 15 10 μ" GOLD OVER NICKEL (RoHS)

**SPECIFY CONTACT FINISH:**

01 200 μ" TIN/LEAD OVER NICKEL

◆ 80 200 μ" TIN OVER NICKEL (RoHS)

◆ 27 30 μ" GOLD OVER NICKEL (RoHS)

**SELECT CONTACT:**

**#34 CONTACT (DATA ON PAGE 258)**

(For alternate contact choices, see group E on page 248)



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Mill-Max:

[0373-0-15-80-34-80-10-0](#) [0373-0-15-80-34-27-10-0](#) [0357-0-15-80-34-80-10-0](#) [0357-0-15-80-34-27-10-0](#) [0351-0-15-80-34-80-10-0](#) [0351-0-15-80-34-27-10-0](#) [0345-0-15-80-34-80-10-0](#) [0345-0-15-80-34-27-10-0](#) [0340-0-15-80-34-80-10-0](#) [0340-0-15-80-34-27-10-0](#) [0334-0-15-80-34-80-10-0](#) [0334-0-15-80-34-27-10-0](#) [0333-0-42-80-34-80-10-0](#) [0333-0-42-80-34-27-10-0](#) [0328-0-15-80-34-80-10-0](#) [0328-0-15-80-34-27-10-0](#) [0327-0-15-80-34-80-10-0](#) [0327-0-15-80-34-27-10-0](#) [0317-0-15-80-34-80-10-0](#) [0317-0-15-80-34-27-10-0](#) [0316-0-15-80-34-27-10-0](#) [0314-0-15-80-34-80-10-0](#) [0314-0-15-80-34-27-10-0](#) [0312-0-15-80-34-27-10-0](#) [0314-0-15-15-34-27-10-0](#) [0328-0-15-15-34-27-10-0](#) [0316-0-15-15-34-27-10-0](#) [0327-0-15-15-34-27-10-0](#) [0317-0-15-15-34-27-10-0](#) [0314-0-15-01-34-01-10-0](#) [0314-0-15-01-34-14-10-0](#) [0314-0-15-01-34-27-10-0](#) [0357-0-15-01-34-27-10-0](#) [0333-0-42-01-34-27-10-0](#) [0312-0-15-01-34-01-10-0](#) [0317-0-15-01-34-01-10-0](#) [0317-0-15-01-34-27-10-0](#) [0317-0-15-01-34-14-10-0](#) [0316-0-15-01-34-27-10-0](#) [0327-0-15-01-34-27-10-0](#) [0328-0-15-01-34-27-10-0](#) [0328-0-15-01-34-01-10-0](#) [0373-0-15-01-34-27-10-0](#) [0345-0-15-15-34-27-10-0](#) [0373-0-15-01-34-01-10-0](#) [0357-0-15-01-34-01-10-0](#) [0351-0-15-01-34-01-10-0](#) [0351-0-15-01-34-27-10-0](#) [0345-0-15-01-34-01-10-0](#) [0345-0-15-01-34-27-10-0](#) [0340-0-15-01-34-01-10-0](#) [0340-0-15-01-34-27-10-0](#) [0334-0-15-01-34-01-10-0](#) [0334-0-15-01-34-27-10-0](#) [0333-0-42-01-34-01-10-0](#) [0327-0-15-01-34-01-10-0](#) [0327-0-15-01-34-14-10-0](#) [0316-0-15-01-34-01-10-0](#) [0357-0-15-15-34-27-10-0](#) [0312-0-15-15-34-27-10-0](#) [0314-0-15-00-00-00-10-0](#) [0327-0-15-00-00-00-10-0](#) [0328-0-15-00-00-00-10-0](#) [0334-0-15-00-00-00-10-0](#) [0340-0-15-15-34-27-10-0](#) [0345-0-15-00-00-00-10-0](#) [0351-0-15-15-34-27-10-0](#) [0357-0-15-00-00-00-10-0](#) [0373-0-15-15-34-27-10-0](#) [0314-0-15-15-24-27-10-0](#) [0314-0-15-01-34-35-10-0](#) [0334-0-15-01-34-14-10-0](#) [0373-0-15-80-34-14-10-0](#) [0327-0-15-80-34-14-10-0](#) [0312-0-15-01-34-14-10-0](#) [0351-0-15-80-34-14-10-0](#) [0333-0-42-01-34-14-10-0](#) [0340-0-15-01-34-14-10-0](#) [0357-0-15-01-34-14-10-0](#) [0345-0-15-01-34-14-10-0](#) [0345-0-15-80-34-14-10-0](#) [0316-0-15-80-34-14-10-0](#) [0317-0-15-80-34-14-10-0](#) [0314-0-15-80-34-14-10-0](#) [0316-0-15-01-34-14-10-0](#) [0312-0-15-80-34-14-10-0](#) [0328-0-15-80-34-14-10-0](#) [0334-0-15-80-34-14-10-0](#) [0351-0-15-01-34-14-10-0](#) [0328-0-15-01-34-14-10-0](#) [0373-0-15-01-34-14-10-0](#) [0357-0-15-15-34-14-10-0](#) [0357-0-15-80-34-14-10-0](#) [0340-0-15-80-34-14-10-0](#) [0333-0-42-80-34-14-10-0](#) [0345-0-15-15-34-14-10-0](#) [0327-0-15-15-34-14-10-0](#)