EVERLIGHT EVERLIGHT ELECTRONICS CO., LTD.

Technical Data Sheet

0805 Package Chip LED (1.1mm Height)

Features

- Package in 8mm tape on 7" diameter reel.
- Compatible with automatic placement equipment.
- Compatible with infrared and vapor phase reflow

solder process.

- Mono-color type.
- Pb-free.

Descriptions

- The 17-21 SMD Taping is much smaller than lead frame type components, thus enable smaller board size, higher packing density, reduced storage space and finally smaller equipment to be obtained.
- Besides, lightweight makes them ideal for miniature applications. etc.

Applications

- Automotive: backlighting in dashboard and switch.
- Telecommunication: indicator and backlighting in telephone and fax.
- Flat backlight for LCD, switch and symbol.
- General use.
- Indoor signboard use.

Device Selection Guide


	0		
Part No.	Material	Emitted Color	Lens Color
17-21/BHC-XL2M2TY/3T	InGaN	Blue	Water Clear



17-21/BHC-XL2M2TY/3T



Package Outline Dimensions



Note: The tolerances unless mentioned is ± 0.1 mm, Unit = mm

http://www.everlight.com Prepared date: 04-May-2005 EVERLIGHT ELECTRONICS CO.,LTD.

17-21/BHC-XL2M2TY/3T

Absolute Maximum Ratings (Ta=25°C)

ÆRLIGHT

Absolute Maximum Ratings (1a-25 ()					
Parameter	Symbol	Rating	Unit		
Reverse Voltage	VR	5	V		
Forward Current	IF	25	mA		
Operating Temperature	Topr	-40 ~ +85	°C		
Storage Temperature	Tstg	-40 ~ +90	°C		
Soldering Temperature	Tsol	260 (for 5 seconds)	°C		
Electrostatic Discharge	ESD	150	V		
Power Dissipation	Pd	110	mW		
Peak Forward Current (Duty 1/10 @1KHz)	Ifp	100	mA		
Soldering Temperature	Tsol	Reflow Soldering : 260 $^{\circ}$ C for 10 sec. Hand Soldering : 350 $^{\circ}$ C for 3 sec.			

Electro-Optical Characteristics (Ta=25°C)

ÆRLIGHT

Electro optical characteristics (14–20 0)							
Parameter	Symbol	Min.	Тур.	Max.	Unit	Condition	
Luminous Intensity	Iv	14.5		28.5	mcd		
Peak Wavelength	λp		468		nm		
Dominant Wavelength	λd	465		470	nm	T C A	
Spectrum Radiation Bandwidth	$ riangle \lambda$		25		nm	IF=5mA	
Viewing Angle	2 0 1/2		140		deg		
Forward Voltage	$V_{\rm F}$	2.6		3.0	V		
Reverse Current	Ir			50	μA	V _R =5V	

Notes:

1.Tolerance of Luminous Intensity ±10%

2.Tolerance of Dominant Wavelength ±1nm

3.Tolerance of Forward Voltage ±0.05V

EVERLIGHT ELECTRONICS CO.,LTD.

17-21/BHC-XL2M2TY/3T

Bin Rang Of Dom. Wavelength						
Group	Bin	Min	Max	Unit	Condition	
X	Х	465	470	nm	IF=5mA	

Bin Rang Of Luminous Intensity

ÆRLIGHT

Bin	Min	Max	Unit	Condition
L2	14.5	18.0		
M1	18.0	22.5	mcd	IF=5mA
M2	22.5	28.5		

Bin Range Of Forward Voltage

Group	Bin	Min	Max	Unit	Condition	
Т	28	2.6	2.7			
	29	2.7	2.8		T C A	
	30	2.8	2.9	V	IF=5mA	
	31	2.9	3.0			

Notes:

1.Tolerance of Luminous Intensity ±10%

2.Tolerance of Dominant Wavelength ±1nm


3.Tolerance of Forward Voltage $\pm 0.05V$

EVERLIGHT ELECTRONICS CO., LTD.

17-21/BHC-XL2M2TY/3T

Typical Electro-Optical Characteristics Curves

ÆRLIGHT



Everlight Electronics Co., Ltd. Device No. : DSE-171-B02 http://www.everlight.com Prepared date: 04-May-2005 Rev.1 Page: 6 of 11 Prepared by: Ashley Kuo

EVERLIGHT EVERLIGHT ELECTRONICS CO., LTD.


17-21/BHC-XL2M2TY/3T

Label explanation

- **CAT: Luminous Intensity Rank**
- HUE: Dom. Wavelength Rank
- **REF: Forward Voltage Rank**




Reel Dimensions



Note: The tolerances unless mentioned is ± 0.1 mm, Unit = mm


Everlight Electronics Co., Ltd. Device No. : DSE-171-B02 http://www.everlight.com Prepared date: 04-May-2005 Rev.1 Page: 7 of 11 Prepared by: Ashley Kuo

Carrier Tape Dimensions: Loaded quantity 3000 PCS per reel



Note: The tolerances unless mentioned is ± 0.1 mm ,Unit = mm

Moisture Resistant Packaging



http://www.everlight.com Prepared date: 04-May-2005

Reliability Test Items And Conditions

The reliability of products shall be satisfied with items listed below. Confidence level : 90%

LTPD: 10%


No.	Items	Test Condition	Test Hours/Cycles	Sample Size	Ac/Re
1	Reflow Soldering	Temp. : 260°C±5°C Min. 5sec.	6 Min.	22 PCS.	0/1
2	Temperature Cycle	H : +100°C 15min $\int 5 \text{ min}$ L : -40°C 15min	300 Cycles	22 PCS.	0/1
3	Thermal Shock	H: +100°C 5min $\int 10 \sec$ L: -10°C 5min	300 Cycles	22 PCS.	0/1
4	High Temperature Storage	Temp. : 100°C	1000 Hrs.	22 PCS.	0/1
5	Low Temperature Storage	Temp. : -40°℃	1000 Hrs.	22 PCS.	0/1
б	DC Operating Life	$I_F = 20 \text{ mA}$	1000 Hrs.	22 PCS.	0/1
7	High Temperature / High Humidity	85℃/ 85%RH	1000 Hrs.	22 PCS.	0/1

Precautions For Use

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

- 2. Storage
 - 2.1 Do not open moisture proof bag before the products are ready to use.
- 2.2 Before opening the package: The LEDs should be kept at 30° C or less and 90%RH or less.
- 2.3 After opening the package : The LEDs should be kept at 30°C or less and 70%RH or less(Floor life). However, it's recommended that the LEDs should be used within 168 hours (7 days) after opening the package. If unused LEDs remain, it should be stored in moisture proof packages.
- 2.4 If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions.Baking treatment : 60±5°C for 24 hours.
- 3. Soldering Condition
 - 3.1 Pb-free solder temperature profile




- 3.2 Reflow soldering should not be done more than two times.
- 3.3 When soldering, do not put stress on the LEDs during heating.
- 3.4 After soldering, do not warp the circuit board.

4.Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than 350° C for 3 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.



EVERLIGHT ELECTRONICS CO., LTD. Office: No 25, Lane 76, Sec 3, Chung Yang Rd, Tucheng, Taipei 236, Taiwan, R.O.C *Tel:* 886-2-2267-2000, 2267-9936 *Fax:* 886-2267-6244, 2267-6189, 2267-6306 *http://www.everlight.com*

Everlight Electronics Co., Ltd. Device No. : DSE-171-B02 http://www.everlight.com Prepared date: 04-May-2005 Rev.1 Page: 11 of 11 Prepared by: Ashley Kuo