

**Micro Commercial Components** 



Micro Commercial Components 130 W Cochran St, Unit B Simi Valley, CA 93065 Tel:818-701-4933

# **MMBT4401**

## **Features**

- Halogen free available upon request by adding suffix "-HF"
- Lead Free Finish/RoHS Compliant ("P" Suffix designates RoHS Compliant. See ordering information)
- Capable of 350mWatts of Power Dissipation and 600mA Ic
- Operating and Storage Junction Temperatures: -55°C to 150°C
- Thermal Resistance Junction to Ambient: 357°C/W
- Epoxy meets UL 94 V-0 flammability rating
- Moisure Sensitivity Level 1
- Marking: 2X/M4A

## **Electrical Characteristics @ 25°C Unless Otherwise Specified**

Symbol	Parameter	Min	Max	Units	
OFF CHARA	OFF CHARACTERISTICS				
V <sub>(BR)CEO</sub>	Collector-Emitter Breakdown Voltage* (I <sub>C</sub> =1.0mAdc, I <sub>B</sub> =0)	40		Vdc	
V <sub>(BR)CBO</sub>	Collector-Base Breakdown Voltage (I <sub>C</sub> =10mAdc, I <sub>E</sub> =0)	60		Vdc	
V <sub>(BR)EBO</sub>	Emitter-Base Breakdown Voltage (I <sub>E</sub> =0.1mAdc, I <sub>C</sub> =0)	6.0		Vdc	
I <sub>BL</sub>	Base Cutoff Current (V <sub>CE</sub> =35Vdc, V <sub>BE</sub> =0.4Vdc)		0.1	μAdc	
I <sub>CEX</sub>	Collector Cutoff Current (V <sub>CE</sub> =35Vdc, V <sub>BE</sub> =0.4Vdc)		0.1	μAdc	

### **ON CHARACTERISTICS**

h <sub>FE</sub>	DC Current Gain*			
	$(I_C=0.1 \text{mAdc}, V_{CE}=1.0 \text{Vdc})$	20		
	(I <sub>C</sub> =1.0mAdc, V <sub>CE</sub> =1.0Vdc)	40		
	(I <sub>C</sub> =10mAdc, V <sub>CE</sub> =1.0Vdc)	80		
	(I <sub>C</sub> =150mAdc, V <sub>CE</sub> =1.0Vdc) 100 300			
	(I <sub>C</sub> =500mAdc, V <sub>CE</sub> =1.0Vdc)	40		
V <sub>CE(sat)</sub>	Collector-Emitter Saturation Voltage			
	$(I_C=150 \text{mAdc}, I_B=15 \text{mAdc})$		0.4	Vdc
	$(I_C=500\text{mAdc}, I_B=50\text{mAdc})$		0.75	
$V_{BE(sat)}$	Base-Emitter Saturation Voltage			
	(I <sub>C</sub> =150mAdc, I <sub>B</sub> =15mAdc)	0.75	0.95	Vdc
	(I <sub>C</sub> =500mAdc, I <sub>B</sub> =50mAdc)		1.2	

## **SMALL-SIGNAL CHARACTERISTICS**


f <sub>T</sub>	Current Gain-Bandwidth Product	250		N 41 1-
	$(I_C=20 \text{mAdc}, V_{CE}=10 \text{Vdc}, f=100 \text{MHz})$	250		MHz
$C_{cb}$	Collector-Base Capacitance			
	$(V_{CB}=5.0Vdc, I_{E}=0, f=1.0MHz)$		6.5	pF
$C_{\sf eb}$	Emitter-Base Capacitance			
	$(V_{BE}=0.5Vdc, I_{C}=0, f=1.0MHz)$		30.0	pF

### **SWITCHING CHARACTERISTICS**

$t_{d}$	Delay Time	(V <sub>CC</sub> =30Vdc, V <sub>BE</sub> =0.2Vdc	15	ns
t <sub>r</sub>	Rise Time	I <sub>C</sub> =150mAdc, I <sub>B1</sub> =15mAdc)	20	ns
ts	Storage Time	(V <sub>CC</sub> =30Vdc, I <sub>C</sub> =150mAdc	225	ns
t <sub>f</sub>	Fall Time	$I_{B1}=I_{B2}=15$ mAdc)	30	ns

<sup>\*</sup>Pulse Width ≤ 300µs, Duty Cycle ≤ 2.0%

# NPN General Purpose Amplifier





DIMENSIONS					
	INCHES		MM		
DIM	MIN	MAX	MIN	MAX	NOTE
Α	.110	.120	2.80	3.04	
В	.083	.104	2.10	2.64	
C	.047	.055	1.20	1.40	
D	.035	.041	.89	1.03	
Е	.070	.081	1.78	2.05	
F	.018	.024	.45	.60	
G	.0005	.0039	.013	.100	
Ι	.035	.044	.89	1.12	
J	.003	.007	.085	.180	
K	.015	.020	.37	.51	


# Suggested Solder Pad Layout O31 O35 900 O35 900 Inches mm


# MMBT4401



















# MMBT4401









### Ordering Information:

Device	Packing
Part Number-TP	Tape&Reel 3Kpcs/Reel

Note: Adding "-HF" suffix for halogen free, eg. Part Number-TP-HF

### \*\*\*IMPORTANT NOTICE\*\*\*

**Micro Commercial Components Corp.** reserves the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes. **Micro Commercial Components Corp.** does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold **Micro Commercial Components Corp.** and all the companies whose products are represented on our website, harmless against all damages.

### \*\*\*LIFE SUPPORT\*\*\*

MCC's products are not authorized for use as critical components in life support devices or systems without the express written approval of Micro Commercial Components Corporation.

#### \*\*\*CUSTOMER AWARENESS\*\*\*

Counterfeiting of semiconductor parts is a growing problem in the industry. Micro Commercial Components (MCC) is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. MCC strongly encourages customers to purchase MCC parts either directly from MCC or from Authorized MCC Distributors who are listed by country on our web page cited below. Products customers buy either from MCC directly or from Authorized MCC Distributors are genuine parts, have full traceability, meet MCC's quality standards for handling and storage. MCC will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. MCC is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.