

# **POWER TRANSFORMER Chassis Mount : International Series**

# VPL24-1100

### **Electrical Specifications (@25C)**

- 1. Maximum Power: 25.0VA
- 2. Input Voltage Series: 230VAC @ 50/60Hz, Parallel: 115VAC@ 50/60Hz
- 3. Output Voltage Series1: 24.0V CT@ 1.040A, Parallel2: 12.0V @ 2.080A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.
- 6. Recommended Fuse<sup>3</sup>:

Series: Littelfuse p/n 313 1.25HXP, 1.25A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BK/MDL-1 ¼, 1.25A 250V, ¼ x 1 ¼ Parallel: Littelfuse p/n 313 2.5HXP, 2.5A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BK/MDL-2 ½, 2.5A 250V, ¼ x 1 ¼

#### **Construction:**

Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

#### **Agency Files:**

UL File: E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 cUL: File E65390, For Canadian Use (CSA 22.2, No.66.1-06 and No.66.3-06) TUV: File R72182067, EN 61558-1:2005+A1, EN61558-2-6:2009. Double Insulated. Non-inherently Short-Circuit-Proof.



Dimen	sions:		Units: In inches		
А	В	С	D	E	F
1.937	3.250	2.125	2.812	8.00	0.187

Weight: 1.3 lbs.

#### Connections<sup>4</sup>:

Input: Series – BLK to BLU, Jumper WHT to BRN Parallel – BLK to BLU, Jumper BLK to BRN and WHT to BLU

Output: Series – RED to GRY, Jumper YEL to VIO Parallel – RED to GRY, Jumper RED to VIO and YEL to GRY

**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative. \* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


- <sup>2</sup> Non-Inherently limited. Class 2 not wet, Class 3 wet.
- <sup>3</sup> Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.


<sup>4</sup> Primary and secondary windings are designed to be connected in series or parallel. Windings are not intended to be used independently.


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571









## SCHEMATIC

Publish Date: August 30, 2021

<sup>&</sup>lt;sup>1</sup> Non-Inherently limited. Class 3.